



Model		Artera Play+	
General Description		CD Player, DAC, Pre-Amp	
Key Technology & Features		DSD (up to DSD256 Compatible) Bluetooth aptX	
Audio File Formats		ALAC, WAV, FLAC, AIFF, WMA, MP3, AAC, AAC- HE, AAC+, DSD64, DSD128, DSD256	
D/A Converter		ESS ES9018 32bit DAC	
USB Input		USB B (PC / MAC)	
Digital Audio Inputs		2 × OpticalTOSlink, 2 × RCA(DIG1, DIG2)	
Digital Audio Outputs		1 × OpticalTOSlink, 1 x RCA (DIG)	
Analogue Inputs		2 × RCA(AUX1, AUX2)	
Analogue Outputs		2 x RCA, 2 x Balanced XLR, 6.3mm Headphone Jack	
Sample Rate (USB B)		44.1kHz, 48kHz, 88.2kHz, 96kHz, 176.4kHz, 192kHz, 384kHz	
Sample Rate (USB A)		44.1kHz, 48kHz	
Sample Rate (Digital Inputs / Outputs)		44.1 - 192kHz	
Standby Power Consumption		<0.5W	
Pre-Amplifier Section			
Output Level (1kHz) Variable Output		0 - 4 Vrms (Pre Outputs) 0 – 8 Vrms (Balanced Outputs)	
Frequency Response		20Hz-20kHz, 1kHz (± 0.2dB)	
Total Harmonic Distortion		<0.002% (20Hz-20kHz)	
Signal to Noise Ration(S/N)		>103dB (1kHz) >110dB (A Weighted, 1kHz)	
Channel Separation		>100dB (1kHz)	
Dimensions (Unpacked) (H x W x D)		320 x 105 x 320mm	
Net Weight		9.04kg	